ROITHNER LASERTECHNIK GmbH
WIEDNER HAUPTSTRASSE 76 1040 VIENNA AUSTRIA
TEL. +43 1 586 52 43 -0, FAX. -44 OFFICE@ROITHNER-LASER.COM

Rev. A2

LED570-03

- Green LED
- 570 nm, 0.75 mW
- Chip: AlGaInP, 300 x 300 µm, 1 pc.
- 5 mm Clear Molding, Epoxy Resin
- Viewing Angle: 24°

RoHS COMPLIANT Pb-Free

Description

LED570-03 contains one AlGaInP LED chip die with a typical peak wavelength of **570 nm** and radiation power of **0.75 mW**. It comes in Ø5 mm clear molding package with soldered lead frame (lead free) and lens molded with epoxy resin.

Maximum Ratings (T_{CASE}=25°C)

Parameter	Symbol	Values Min.	Values Max.	Unit
Power Dissipation	P_D		50	mW
Forward Current	I_F		20	mA
Pulse Forward Current *1	I_{FP}		100	mA
Reverse Voltage	V_R		5	V
Thermal Resistance	R_{THJA}		300	K/W
Junction Temperature	T_J		100	°C
Operating Temperature	T_{CASE}	- 40	+ 85	°C
Storage Temperature	T_{STG}	- 40	+ 100	°C
Lead Solder Temperature *2	T_{SLD}		+ 265	°C

*1 *duty=1%, pulse width = 10 µs*
*2 *must be completed within 5 seconds*

Electro-Optical Characteristics (T_{CASE}=25°C)

Parameter	Symbol	Conditions	Min.	Typ.	Max.	Unit
Peak Wavelength	λ_P	I_F=20mA	560		580	nm
Dominant Wavelength	λ_D	I_F=20mA		568		
Half Width	$\Delta\lambda$	I_F=20mA		11		nm
Forward Voltage	V_F	I_F=20mA		2.1	2.3	V
	V_{FP}	I_{FP}=100mA		2.3		
Radiated Power *1	P_O	I_F=20mA		0.75		mW
		I_{FP}=100mA		4.0		
Radiant Intensity *2	I_E	I_F=20mA		3.9		mW/sr
		I_{FP}=100mA		21		
Luminous Flux	ΦV	I_F=20mA		500		mlm
Viewing Angle	$2\theta_{1/2}$	I_F=20mA		24		deg.
Rise Time	t_r	I_F=20mA		50		ns
Fall Time	t_f	I_F=20mA		30		ns

*1 *measured by S3584-08*
*2 *measured by CIE127-2007 Condition B*

ROITHNER LASERTECHNIK GmbH
WIEDNER HAUPTSTRASSE 76 1040 VIENNA AUSTRIA
TEL. +43 1 586 52 43 -0, FAX. -44 OFFICE@ROITHNER-LASER.COM

Typical Performance Curves

Forward Current vs. Forward Voltage



Rel. Radiant Intensity vs. Forward Current



Forward Current vs. Pulse Duration



Allowed Forward Current vs. Ambient Temperature



Forward Voltage vs. Ambient Temperature



Rel. Radiant Intensity vs. Ambient Temperature



ROITHNER LASERTECHNIK GmbH
WIEDNER HAUPTSTRASSE 76 1040 VIENNA AUSTRIA
TEL. +43 1 586 52 43 -0, FAX. -44 OFFICE@ROITHNER-LASER.COM

Peak Wavelength vs. Ambient Temperature



Relative Spectral Emission



Radiation Characteristics



Radiation Characteristics



Outline Dimensions

LED570-03 **5 mm**



Lead	Description
Short Pin	LED Cathode
Long Pin	LED Anode

All Dimensions in mm

Precautions

Soldering:

- Do avoid overheating of the LED
- Do avoid electrostatic discharge (ESD)
- Do avoid mechanical stress, shock, and vibration
- Do only use non-corrosive flux
- Do not apply current to the LED until it has cooled down to room temperature after soldering

Recommended soldering conditions:

Soldering Conditions



Recommended Soldering Patterns



Unit: mm

Above table specifies the maximum allowed duration and temperature during soldering. It is strongly advised to perform soldering at the shortest time and lowest temperature possible.

Cleaning:

Cleaning with isopropyl alcohol, propanol, or ethyl alcohol is recommended
DO NOT USE acetone, chloroseen, trichloroethylene, or MKS
DO NOT USE ultrasonic cleaners

Static Electricity:

LEDs are sensitive to electrostatic discharge (ESD). Precautions against ESD must be taken when handling or operating these LEDs. Surge voltage or electrostatic discharge can result in complete failure of the device.

Radiation:

During operation these LEDs do emit light, which could be hazardous to skin and eyes, and may cause cancer. Do avoid exposure to the emitted light. Protective glasses if needed. It is further advised to attach a warning label on products/systems.

Operation:

Do *only* operate LEDs with a current source.
Running these LEDs from a voltage source will result in complete failure of the device.
Current of a LED is an exponential function of the voltage across it. Usage of current regulated drive circuits is mandatory.

Revisions History

Rel.	Rel. Date	Chapter	Modification	Page
A2	*2020-06-30*	Typical Performance Curves	Forward Current vs. Pulse Duration Duration tw: µs *(previously ms)*	2
A1	*2020-05-20*	-	Initial release	-