ROITHNER LASERTECHNIK GmbH
WIEDNER HAUPTSTRASSE 76 1040 VIENNA AUSTRIA
TEL. +43 1 586 52 43 -0, FAX. -44 OFFICE@ROITHNER-LASER.COM

2017 / 05

SMB1N-D630

- Red High Power LED
- 630 nm, 290 mW
- SMD package, PA9T
- Dimension: 5.0 x 5.2 x 1.0 mm
- Viewing Angle: 128°

RoHS COMPLIANT Pb-Free

Description

SMB1N-D630 is a surface mount AlGaInP High Power LED with a typical peak wavelength of **630 nm** and radiation of **290 mW**. It comes in SMD package (PA9T) with silver plated soldering pads (lead free solderable), copper heat sink, and molded with silicone resin.

Maximum Ratings (T_{CASE}=25°C)

Parameter	Symbol	Values Min.	Values Max.	Unit
Power Dissipation	P_D		1000	mW
Forward Current	I_F		350	mA
Pulse Forward Current *1	I_{FP}		500	mA
Reverse Voltage	V_R		5	V
Thermal Resistance	R_{THJA}		10	K/W
Junction Temperature	T_J		120	°C
Operating Temperature	T_{CASE}	- 40	+ 100	°C
Storage Temperature	T_{STG}	- 40	+ 100	°C
Lead Solder Temperature *2	T_{SLD}		+ 250	°C

*1 *duty=1%, pulse width = 10 µs*
*2 *must be completed within 5 seconds*

Electro-Optical Characteristics (T_{CASE}=25°C)

Parameter	Symbol	Conditions	Min.	Typ.	Max.	Unit
Peak Wavelength	λ_P	I_F=350mA	620		640	nm
Dominant Wavelength	λ_D	I_F=350mA		620		nm
Half Width	$\Delta\lambda$	I_F=350mA		15		nm
Forward Voltage	V_F V_{FP}	I_F=350mA I_{FP}=500mA		2.3 2.5	2.8	V
Radiated Power *1	P_O	I_F=350mA I_{FP}=500mA		190 410		mW
Radiant Intensity *2	I_E	I_F=350mA I_{FP}=500mA		96 130		mW/sr
Luminous Flux	Φv	I_F=350mA		50		lm
Viewing Angle	φ	I_F=100mA		128		deg.
Rise Time	t_R	I_F=350mA		80		ns
Fall Time	t_F	I_F=350mA		40		ns

*1 *measured by S3584-08*
*2 *measured by CIE127-2007 Condition B*

ROITHNER LASERTECHNIK GmbH
WIEDNER HAUPTSTRASSE 76 1040 VIENNA AUSTRIA
TEL. +43 1 586 52 43 -0, FAX. -44 OFFICE@ROITHNER-LASER.COM

Typical Performance Curves

Forward Current vs. Forward Voltage



Rel. Radiant Intensity vs. Forward Current



Forward Current vs. Pulse Duration



Allowed Forward Current vs. Ambient Temperature



Forward Voltage vs. Ambient Temperature



Rel. Radiant Intensity vs. Ambient Temperature



ROITHNER LASERTECHNIK GmbH
WIEDNER HAUPTSTRASSE 76 1040 VIENNA AUSTRIA
TEL. +43 1 586 52 43 -0, FAX. -44 OFFICE@ROITHNER-LASER.COM

Peak Wavelength vs. Ambient Temperature



Relative Spectral Emission



Radiation Characteristics



Radiation Characteristics



Outline Dimensions

SMB1N **flat**



Lead	Description
Pin a1	LED Anode
Pin c1	LED Cathode

All Dimensions in mm

Precautions

Soldering:

- Do avoid overheating of the LED
- Do avoid electrostatic discharge (ESD)
- Do avoid mechanical stress, shock, and vibration
- Do only use non-corrosive flux
- Do not apply current to the LED until it has cooled down to room temperature after soldering

Recommended soldering conditions:

This LED is designed to be reflow soldered on to a PCB. If dip soldered or hand soldered, its reliability cannot be guarantee.
Nitrogen reflow soldering is recommended. Air flow soldering conditions can cause optical degradation, caused by heat and/or atmosphere.

IR Reflow Soldering Profile (Lead-free Solder)



Recommended Soldering Patterns



Above table specifies the maximum allowed duration and temperature during soldering. It is strongly advised to perform soldering at the shortest time and lowest temperature possible.

Cleaning:

Cleaning with isopropyl alcohol, propanol, or ethyl alcohol is recommended
DO NOT USE acetone, chloroseen, trichloroethylene, or MKS
DO NOT USE ultrasonic cleaners

Static Electricity:

LEDs are sensitive to electrostatic discharge (ESD). Precautions against ESD must be taken when handling or operating these LEDs. Surge voltage or electrostatic discharge can result in complete failure of the device.

Radiation:

During operation these LEDs do emit **high intensity light**, which is hazardous to skin and eyes, and may cause cancer. Do avoid exposure to the emitted light. **Protective glasses are recommended**. It is further advised to attach a warning label on products/systems.

Operation:

Do *only* operate LEDs with a current source.
Running these LEDs from a voltage source will result in complete failure of the device.
Current of a LED is an exponential function of the voltage across it. Usage of current regulated drive circuits is mandatory.

ROITHNER LASERTECHNIK GmbH
WIEDNER HAUPTSTRASSE 76 1040 VIENNA AUSTRIA
TEL. +43 1 586 52 43 -0, FAX. -44 OFFICE@ROITHNER-LASER.COM

Revisions History

Rel.	Rel. Date	Chapter	Modification	Page
	2017 05	-	released	-

© All Rights Reserved
The above specifications are for reference purpose only and subjected to change without prior notice